



| No | Denominazione | Valv. | Plac. | Scher. | Catod. | Griegl. | Filam. |
|----|----------------|-------|-------|--------|--------|---------|--------|
| 1 | Sovrappositr. | 6BE6 | 152 | 100 | 100 | 100 | 6,6 |
| 2 | Amplific.MF | 6BA6 | 152 | 100 | 100 | 100 | 6,6 |
| 3 | Demod.ampl.BF | 6AT6 | 63 | 152 | 152 | 152 | 6,6 |
| 4 | Finale | 6AQ5 | 223 | 152 | 152 | 152 | 6,6 |
| 5 | Raddrizzatr. | 6X4 | 216 | 152 | 152 | 152 | 6,6 |
| 6 | Indicat.sinton | DM70 | 53 | 152 | 152 | 152 | 6,6 |

* G11 altoparlanti devono essere in fase

UNDA RADIO - Mod. R 66/5. Radiofonografo soprammobile a 6 gamme d'onda: 182-578 m. e bande allargate di 19-25-31-49-75 m. Potenza d'uscita 3,5 watt. Consumo CC 52 mA. CA 190 mA. Watt 40, in radio. In fono: CA 220 mA, 47 watt. Media freq 467 kc/s.

UNDA RADIO - Mod. R 66/5

UNDA RADIO - Mod. R 66/5